



LOCKDOWN



Secure any door

Protect schools, places of worship, safe rooms, and more



Z-Wave Plus

Easy to pair and control, expand the mesh network with additional Z-wave devices



Easy Installation

Installs in less than 25 minutes, no power run needed.



Code Compliant

FCC, 2018 Life Safety Compliant, NFPA, ADA, UL Standard Tested by a NRTL



Stronger than a Deadbolt

10x stronger than a conventional lock, providing time for police to arrive.



Battery Powered

Long lasting internal rechargeable LiPo battery, no power run required.



SPECIFICATIONS

Items	Parameters	IQ Lockdown
Z-Wave Plus	Easy to Pair	Utilize the Mesh network by adding additional Z-wave devices to expand range.
Multiple	Locks	Connect up to 20 Locks to a single IQ Panel
Battery	Rechargeable	Long life internal rechargeable LiPo battery. Main battery lasts for 3-5 months on a single charge under normal use. Please charge your unit every two to three months. Charge via USB cable.
Mechanical	Dimensions	15.5"L x 45"W x 4.1"H
Power Supply	Charging	120v AC USB Adapter for use with included USB charging cable
Mount	Door	Works on both outward and inward swinging doors. Designed to be installed onto a standard 2" door frame, backed with poured concrete. If installing onto hollow door frame use the hollow door frame kit hardware kit, sold separately.
Equipment	Materials	Military grade materials and testing
Code	Requirement	FCC, 2018 Life Safety Compliant NFPA, ADA Compliant, UL Standard Tested by a NRTL, Independent Strength Testing
Remote	Control	Using IQ Panel or Alarm.com app, device can be locked and unlocked.
Manual	Control	Device can be manually locked or unlocked at the unit or by egress button (optional)

